



UNIT	A	B	D	E	F	G	H	J	N	O
G0302A	5.31	5.16	2.95	4.33	4.33	.47	.39	.98	1.57	5.79
G0402A	5.71	6.30	3.54	4.33	5.12	.62	.39	1.38	1.97	7.01
G0602A	7.48	7.88	4.53	5.31	6.50	.79	.59	2.17	2.36	9.06
G0702A	9.06	9.65	5.51	6.69	8.07	.98	.75	2.36	3.15	10.83
G0802A	11.42	12.20	7.09	8.46	10.24	1.38	.75	2.95	3.94	14.25

UNIT	U	AD	AE	BA	ES	X-TAP	SQ. KEY
G0302A	.7500	3.07	2.83	2.28	1.28	1/4-28 TAP	.19
G0402A	1.0000	3.31	2.95	2.95	1.75	1/4-28 TAP	.25
G0602A	1.3750	4.13	3.86	3.94	2.00	3/8-24 TAP	.31
G0702A	1.6250	5.12	4.69	4.53	2.38	5/8-18 TAP	.38
G0802A	2.1250	6.50	5.79	5.51	2.75	5/8-18 TAP	.50

UNIT	C DIMENSION BY INPUT MOTOR FRAME			
	140TC	180TC	210TC	250TC
G0302A	9.02	9.44	-	-
G0402A	9.92	10.35	-	-
G0602A	11.38	13.00	13.00	-
G0702A	14.29	15.09	15.09	15.09
G0802A	17.69	17.69	17.69	17.69

FRAME	C-FACE INPUT DIMENSIONS BY MOTOR FRAME					
	FAK	FAJ	FBD	FBF	FU	
56C	4.500	5.88	6.50	.41	.625	
140TC	4.500	5.88	6.50	.41	.875	
180TC	8.500	7.25	9.00	.53	1.125	
210TC	8.500	7.25	9.00	.53	1.375	
250TC	8.500	7.25	10.00	.53	1.625	

FRAME	MOTOR FRAME	
	P	AG
56C	7.31	10.70
140TC	7.88	10.70
180TC	8.85	12.31
210TC	11.25	16.34
250TC	12.52	20.68